قم بشبك الفقل على البلوتوث من خلال التطبيق يمكن للمسؤول إدخال كلمة المرور

اضغط على "إضافة كلمة المرور" للدخول إلى صفحة إدخال كلمة المرور، الإنشاء

سيؤدي إلى إطلاق جرس الإنذار في التطبيق، وينطبق أيضاً على البصمات

إدارة بطاقات الباب:

بواسطة توصيل القفل عبر تطبيق البلوتوث، يمكن للمسؤول إدخال بطاقة الباب لنفسه أو لأفراد العائلة الآخرين؛ قبل إضافة بطاقة الباب، يجب تحديد المستخدم المقابل لإضافتها، ثم انقر على "إضافة بطاقة الباب" للدخول إلى واجهة إدخال البطاقة، وضع القفل على منطقة الاستشعار المقابلة للإدخال عن طريق السحب.

إدارة الرموز المؤقتة:

ً الرمز المتصل Online: عند توصيل القفل عبر التطبيق، يمكن للمسؤول إدخال كلمة

الرمز غير متصل Offline: في حالة عدم الاتصال بالبلوتوث، يمكنك إنشاء رمز مؤقت لمرة واحدة، إلكتروني ورمز مسح. ويتم إنشاءها عشوائياً بدون إعدادها.

تحكّم المستخدمين من أفراد العائلة:

إضافته، ويحتفظ العضو بصلاحية الاستخدام المناسبة حتى يقوم المسؤول بحذفه.

2. طريقة فتح الأبواب: يحدّد المسؤول نوع صلاحية المستخدمين لفتح الأبواب؛ في حالة إيقاف جميع صلاحيات الفتح فإن المستخدم لن يكون قادراً على فتح الأبواب من خلال التطبيق ولا يمكنه الاستخدام إلا بالطريقة المعرّفة حالياً.

إدارة المستخدمين الآخرين:

1. فترة الصلاحية: يحدد المسؤول فترة الصلاحية للمستخدمين الآخرين، ويمكن تعيينها إما دائمة، أو مؤقتة.

يصل المستخدم إلى وقت الانتهاء المحدد، سيفقد تطبيق المستخدم الجهاز تلقائياً.

يمكنك الاستعلام عن سجل الفتح في "سجل فتح الباب"، وتتم ترتيب السجلات

عرض سجل الفتح:

عندما يتم ربط الباب بتقنية البلوتوث سيتم عرض سجل فتح الباب على التطبيق، في البلوتوث والفتح لإضافة النقل.

تعيين وضع الفتح:

أ. ضبط الصفحة الرئيسية: يمكنك الإعداد بصمة، كلمة مرور، بطاقة الدخول، كلمة مرور مؤقتة، قفل تلقائي، ضبط الصوت. ب. إذا قمت بتشغيل وضع القفل التلقائي، سيتم إقفال الباب تلقائياً بعد خمس ثوانٍ من الفتح. في حالة إيّقاف هذا الإعداد، سيتم العودة إلى وضع الفتح العادي.

من خلال توصيل القفل عبر البلوتوث ، يمكن للمسؤول جمع البصمات لنفسه أو اختر "بدء الجمع" للدخول إلى واجهة تعيين البصمة، كل تعيين لبصمة يحتاج إلى

تعريف الجهاز على تطبيق Orange Smart Life Jo 1. قم بتشغيل الجهاز من خلال منفذ USB أو البطارية) وقم بتشغيل البلوتوث على

2. اضغط على زر إعادة الضبط (داخل مقبض اليد الداخلي للجهاز) لمدة 5 ثوانٍ، اضغط على مفتاحي "8 + #" لتشغيل البرنامج، وستسمع صوت من الجهاز وتكون 3. اضغط على علامة "+" في الصفحة الرئيسية، واضغط على "إضافة جهاز" وانتظر حتى يظهر اسم الجهاز في الصفحة ثم اضغط على "إضافة".

5. عند إضافة الجهاز بنجاح، والآن انقر على "تم". 6. ستظهر شاشة الجهاز الرئيسية بحيث يمكنك استخدام جميع الخيارات ا<u>لمتاحة</u>.



الميّزات والمعلومات الإضافية:

- حالة الاتصال بالبلوتوث: إذا نجحت بالاتصال بالبلوتوث، فسيتم عرض زر "اضغط - إدارة المستخدمين: يمكنك إضافة المستخدمين من أفراد العائلة أو أي أعضاء

- فتح السجل: يمكنك التحقق من المستخدم الذي قام بفتح الباب وكيفية فتحه. - الإعدادات: يمكنك ضبط البصمات وكلمة المرور، والبطاقة، والقفل، والصوت.

ادارة المستخدمين:

1. أفراد العائلة: يتوافق هذا النوع من الأعضاء مع أفراد العائلة المسجلين في إعدادات "قفل الباب"

ملاحظة: لا يمكن حذف أفراد العائلة إلا من خلال الذهاب إلى خانة "إدارة أفراد

2. المستخدمون الآخرين: يشير إلى المستخدمين الذين يظهرون فقط في إعدادات خانة "قفل الباب"، ولن يكونوا مشمولين في مجموعة "أفراد العائلة" في التطبيق> لن يؤثر إضافة أو حذف المستخدمين على خصائص "مجموعة العائلة".

نركيب الجهاز:

2. ثبّت القفل بالمسمار، تأكد من أن يكون السهم باتجاه الباب 3. ثبّت اللوحة الخلفية 4. قم بتركيب البطارية، وسلك التوصيل لوحة القفل

القطعة

اتّبع الخطوات التالية مع الصور، لعملية التركيب أسهل.





قفل الباب الذكي

تحميل التطبيق

1- حمّل تطبيق Orange Smart Life JO






2. قم بالتسجيل باستخدام بريدك الإلكتروني، حيث إن المستخدم وحده هو المسؤول عن حماية حسابه على تطبيق Orange Smart Life JO، ويُنصح بعدم مشاركة اسم المستخدم وكلمة المرور مع أي شخص. إذ سيكون فريق Orange التقنى مسؤولاً عن توفير الدعم لضبط الأجهزة. 3. اختر (الحصول على رمز)، ليتم إرسال رمز التحقق إلى بريدك الإلكتروني.

4. املأ الرمز المكوّن من ستة أرقام في المكان المخصص. 5. أدخل كلمة المرور الخاصة بك.

6. قبل إعداد أي جهاز، يجب عليك تفعيل ميزة GPS من جهازك المحمول لتكون متصلاً بشبكتك اللاسلكية (الاتصال بشبكة 2.4 جيجا هرتز).

1. احتفظ بالمفتاح التقليدي في الخارج في حالة تم القفل من الداخل أو

2. استبدل البطارية في حال كان إنذار الشحن منخفض القوة. 3. اقرأ هذا الدليل بعناية قبل التركيب واحتفظ به للرجوع إليه عند الحاجة. 4. تأكد من أن العلبة تحتوي على جميع القطع المذكورة أدناه:



















Smart Life Solutions by Orange Smart plugs nergy saving Home cameras Settings §O.§

Smart Door lock





Download the application

1. Download Orange Smart Life JO application





3. Register using your e-mail, as the user alone is responsible for protecting the username and password for Orange Smart Life JO application, and we recommend not to share the username and the password with anyone. Orange technical team will be responsible of providing setup and configuration support for the devices

- 4. Select (Get a code), the verification code will be sent to your
- 5. Fill out the six-digit code in the space provided on the application
- 6. Enter your password
- 7. Before setting up any device, you must activate the GPS feature from your mobile device in order to be connected to your wireless network (Connect to the 2.4GHz network)

Before activating the device, please:

- 1. Keep the mechanical key outdoors in case keys lock indoors.
- 2. Replace the battery when you have a low-wattage alarm. 3. Read this manual carefully before installation and keep it for
- 4. Make sure the package contains all the parts mentioned

Strike & Strike Box Mortise Screws: M5*10mm (For Aluminum Door) 4 M4*40mm Screw M4*50mm Screw

Installing the device

- 2. Install screw casing, make sure the arrow is always up towards the
- 3. Install the back panel

Install the crew Stubs	Paradiana na	Step 2: Install Screw Casing	
step 3: Install Back Panel		Step 4: Install the battery, link wire, and lock	



Device configuration through the Orange Smart Life JO app

1. Power on the device (through USB charging port or battery) and turn

without releasing it, touch the "8 + #" keys to operate the program, you will hear a beeping sound, means reset is done successfully. 3. Tap "+" in the upper right corner of the Home page then tap Add

Device, wait until the device name appears on the page then click Add.

6. The device screen will appear so that you can use all available



Features and additional information

- Opening record: You can check which user opened the door and how.
- Settings: You can set your fingerprints, password, card, auto lock and

Members and management

Two types of members:

the family group in the app. When a new user is added to the family group in the app, one more family member will appear in the door lock

Note: Deleting family members can only be operated in the family

2. Other members: This refers to users who only appear in the door lock, not users in the app family group. Adding or deleting such users will not affect the members of the app family group.

Family members' management

until the administrator deletes the member.

only use the existing door opening method.

1. Validity period: The administrator can determine the length of the validity period for other members. It can be set to be permanently

2. Door-opening method: The administrator can determine the member's members.)

member with a user of the app through the Share operation. When the user reaches the specified end time, the user's app will automatically

arranged in reverse order. The "unlock ID" that has been associated with the user's name will directly display the corresponding user's name. The "unlock ID" that has not been associated with the name will display the specific unlock ID.

About opening log display

door opening record will be displayed on the APP in real time, otherwise,

a. Homepage setting entrance: you can set up fingerprint, password, b. If you turn on the automatic lock setting, the door will be

this setting, the lock will be back to the regular open mode.

card, temporary password, automatic lock, and volume setting.

Fingerprint management

collect fingerprints for himself or other family members. Before collecting, select the corresponding user to the fingerprint so he/she car

Connect the door lock through the app Bluetooth, the administrator can enter the password for himself or other family members; before adding the password, select the user corresponding to the added password. supports random generation and custom passwords. Note: The hijacking password refers to opening the account. Using this

password to open the door will trigger an app hijacking alarm (the same

Door card management

applies to fingerprints and door cards).

enter the door card for himself or other family members; before adding the door card, select the user corresponding to the added door card and

Online Code: By connecting the door lock via Bluetooth app, the administrator can enter a temporary password for himself or other family

Offline Code: When the Bluetooth is not connected, you can generate a passwords are randomly generated and do not need to be set.